

max. 100 m



85421700

DALI/DSI control insert, electronics

Technical characteristics

| Push button r switching and controlling electr. ballasts and Tronic transformer with DALI/DSI interface 50/60 Hz 230 V AC 16 V DC |
|--|
| r switching and controlling electr. ballasts and Tronic transformer with DALI/DSI interface 50/60 Hz 230 V AC 16 V DC |
| Tronic transformer with DALI/DSI interface 50/60 Hz 230 V AC 16 V DC |
| Tronic transformer with DALI/DSI interface 50/60 Hz 230 V AC 16 V DC |
| 230 V AC 16 V DC 40 mA |
| 230 V AC 16 V DC 40 mA |
| 16 V DC |
| 16 V DC |
| 40 mA |
| |
| |
| |
| max. 40 mA |
| |
| 32 mm |
| 32 mm |
| 32 mm |
| 22 mm |
| |
| < 0.4 W |
| |
| with extension unit input for push-button (NC contact) |
| |
| white |
| |
| max. 20 |
| with screw terminals |
| unlimited |
| |
| max. 300 m |
| |

Cable length, extensions

| Yes |
|---|
| max. 64 |
| switch-on brightness level can be stored safe after power failure |
| Bus communication in Broadcast mode according to IEC 62386-102 |
| |
| No |
| Yes |
| No |
| |
| -545 °C |
| -2060 °C |
| 065 % (without condensation) |
| |
| |

Light control, KNX radio- operating systems

Application, usage