



HDA030Z

Moulded Case Circuit Breaker h3 x160 TM FIX 1P1D 32A 18kA CTC

Technical characteristics

Neutral position	without neutral
Number of protected poles	1
Number of poles	1 P
Type of pole	1P1D
Functions	
Trip Unit	TM F/F
Integrated earth fault protection	No
Concurrently switching N-neutral	No
Controls and indicators	
Motor drive integrated	No
Main electrical features	
Rated operational voltage Ue	220 / 240 V
Type of supply voltage	AC
Frequency	50/60 Hz
Voltage	
Rated insulation voltage	690 V
Rated impulse withstand voltage	8 kV
With under voltage release	No
Electric current	
Rated current	32 A
Thermal protection nob setting xIN	1
Rating current 10°C according to IEC 60947	43.8 A
Rating current 15°C according to IEC 60947	42.5 A
Rating current 20°C according to IEC 60947	41.2 A
Rating current 25°C according to IEC 60947	39.8 A
Rating current 30°C according to IEC 60947	38.4 A
Rating current 35°C according to IEC 60947	36.9 A
Rating current 40°C according to IEC 60947	35.3 A
Rating current 45°C according to IEC 60947	33.7 A
Rating current 50°C according to IEC 60947	32 A
Rating current 55°C according to IEC 60947	30.1 A

Breaking capacity on 1 pole for IT 230V NF 60947-2 Rated ultimate short-circuit breaking capacity Icu under 230V AC IEC 60947-2 Range of the thermal adjustment Rated ultimate short-circuit breaking capacity Icu under 240V AC IEC 60947-2 Range of the thermal adjustment Rated ultimate short-circuit breaking capacity Icu under 220V AC IEC 60947-2 Dimensions Depth of installed product Height of installed product Width of installed product Width of installed product Prequency Frequency Prequency Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. rigid cable Type of connection Cable Cable Cable Material Settings Range of the magnetic adjustment	18 kA 18 kA 18 kA 32 A 18 kA 68 mm 130 mm 25 mm 50 to 60 Hz 3 W 3 W 3 W
capacity Icu under 230V AC IEC 60947-2 Rated ultimate short-circuit breaking capacity Icu under 240V AC IEC 60947-2 Range of the thermal adjustment Rated ultimate short-circuit breaking capacity Icu under 220V AC IEC 60947-2 Dimensions Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection Cable Cable Cable Material	18 kA 32 A 18 kA 68 mm 130 mm 25 mm 50 to 60 Hz 3 W 3 W 3 W
capacity Icu under 240V AC IEC 60947-2 Range of the thermal adjustment Rated ultimate short-circuit breaking capacity Icu under 220V AC IEC 60947-2 Dimensions Depth of installed product Height of installed product Height of installed product Frequency Frequency Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection Cable Cable Rate Cable Cable Material Settings	32 A 32 A 18 kA 68 mm 130 mm 25 mm 50 to 60 Hz 3 W 3 W 3 W 1000 4000
Rated ultimate short-circuit breaking capacity icu under 220V AC IEC 60947-2 Dimensions Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Material Settings	18 kA 68 mm 130 mm 25 mm 50 to 60 Hz 3 W 3 W 1000 4000
capacity icu under 220V AC IEC 60947-2 Dimensions Depth of installed product Height of installed product Frequency Frequency Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection Connection Connection Cable Cable Material Settings	68 mm 130 mm 25 mm 50 to 60 Hz 3 W 3 W 1000 4000
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Material Settings	130 mm 25 mm 50 to 60 Hz 3 W 3 W 1000 4000
Height of installed product Width of installed product Frequency Frequency Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Material Settings	130 mm 25 mm 50 to 60 Hz 3 W 3 W 1000 4000
Width of installed product Frequency Frequency Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection Type of connection Cable Cable Material	25 mm 50 to 60 Hz 3 W 3 W 1000 4000
Frequency Frequency Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Material Settings	50 to 60 Hz 3 W 3 W 1000 4000
Frequency Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Material Settings	3 W 3 W 1000 4000
Power Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection Type of connection Cable Cable Settings	3 W 3 W 1000 4000
Total power loss under IN Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Cable Material Settings	3 W 1000 4000
Power loss per pole at In Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Cable Settings	3 W 1000 4000
Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Material Settings	1000 4000
Electric endurance in number of cycles Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Material Settings	4000
Number of mechanical operations Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Material Settings	4000
Installation, mounting Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Material Settings	
Tightening torque Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Material Settings	China
Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Cable Material Settings	
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Cable Cable Settings	
Connection cross-sect. rigid cable Type of connection Cable Cable Material Settings	
Type of connection Cable Cable Material Settings	6 / 70mm²
Cable Cable Material Settings	6 / 95mm²
Cable Material Settings	with screw
Settings	
	Cu
Range of the magnetic adjustment	
	600 A
Equipment	
Number of auxiliary contacts as normally closed contact	C
Number of auxiliary contacts as normally open contact	C
Number of auxiliary contacts as change- over contact	C
Can be accessorized	
Use cases	Yes
Category of use	Yes
Standards	Yes

Safety

Standard text

Yes
Yes
No
3

Altitude

temperatur

Temperature of calibration

2000 m