



HMJ400DR

Moulded Case Circuit Breaker h3 x630 TM ADJ 3P3D 400A 50kA FTC

Technical characteristics

Architectu	re
------------	----

Type of order	Toggle
Neutral position	without neutral
Number of protected poles	3
Number of poles	3 P
Type of pole	3P3D
Fixing mode	fixing plate
Type of case	Fixed built-in
Functions	
Complete device with protection unit	Yes
Version as main switch	Yes
Version as emergency stop installation	No
Version as safety switch	No
Version as maintenance-/service switch	Yes
Trip Unit	TM A/A
Integrated earth fault protection	No
Controls and indicators	
Controls and indicators Motor drive integrated	No
	No
	No
Motor drive integrated	No 220 / 415 V
Motor drive integrated Main electrical features	
Motor drive integrated Main electrical features Rated operational voltage Ue	220 / 415 V
Motor drive integrated Main electrical features Rated operational voltage Ue Type of supply voltage	220 / 415 V AC
Motor drive integrated Main electrical features Rated operational voltage Ue Type of supply voltage Frequency	220 / 415 V AC
Motor drive integrated Main electrical features Rated operational voltage Ue Type of supply voltage Frequency Voltage	220 / 415 V AC 50/60 Hz
Motor drive integrated Main electrical features Rated operational voltage Ue Type of supply voltage Frequency Voltage Rated insulation voltage	220 / 415 V AC 50/60 Hz
Motor drive integrated Main electrical features Rated operational voltage Ue Type of supply voltage Frequency Voltage Rated insulation voltage Rated impulse withstand voltage	220 / 415 V AC 50/60 Hz 800 V 8 kV
Motor drive integrated Main electrical features Rated operational voltage Ue Type of supply voltage Frequency Voltage Rated insulation voltage Rated impulse withstand voltage With under voltage release	220 / 415 V AC 50/60 Hz 800 V 8 kV
Main electrical features Rated operational voltage Ue Type of supply voltage Frequency Voltage Rated insulation voltage Rated impulse withstand voltage With under voltage release	220 / 415 V AC 50/60 Hz 800 V 8 kV No
Main electrical features Rated operational voltage Ue Type of supply voltage Frequency Voltage Rated insulation voltage Rated impulse withstand voltage With under voltage release Electric current Rated current	220 / 415 V AC 50/60 Hz 800 V 8 kV No
Main electrical features Rated operational voltage Ue Type of supply voltage Frequency Voltage Rated insulation voltage Rated impulse withstand voltage With under voltage release Electric current Rated current Thermal protection nob setting xIN	220 / 415 V AC 50/60 Hz 800 V 8 kV No 400 A 0.63 / 0.8 / 1
Main electrical features Rated operational voltage Ue Type of supply voltage Frequency Voltage Rated insulation voltage Rated impulse withstand voltage With under voltage release Electric current Rated current Thermal protection nob setting xIN Rating current 10°C according to IEC 60947	220 / 415 V AC 50/60 Hz 800 V 8 kV No 400 A 0.63 / 0.8 / 1 470.7 A
Main electrical features Rated operational voltage Ue Type of supply voltage Frequency Voltage Rated insulation voltage Rated impulse withstand voltage With under voltage release Electric current Rated current Thermal protection nob setting xIN Rating current 15°C according to IEC 60947 Rating current 15°C according to IEC 60947	220 / 415 V AC 50/60 Hz 800 V 8 kV No 400 A 0.63 / 0.8 / 1 470.7 A 462.5 A

Rating current 35°C according to IEC 60947	427.9 A
Rating current 40°C according to IEC 60947	418.8 A
Rating current 45°C according to IEC 60947	409.5 A
Rating current 50°C according to IEC 60947	400 A
Rating current 55°C according to IEC 60947	390.3 A
Rating current 60°C according to IEC 60947	380.3 A
Rating current 65°C according to IEC 60947	370 A
Rating current 70°C according to IEC 60947	359.4 A
Breaking capacity on 1 pole for IT 230V NF 60947-2	10 kA
Breaking capacity on 1 pole for IT 400V NF 60947-2	10 kA
Breaking capacity on 1 pole for IT 415V NF 60947-2	10 kA
Rated ultimate short-circuit breaking capacity Icu under 230V AC IEC 60947-2	85 kA
Rated ultimate short-circuit breaking capacity Icu under 240V AC IEC 60947-2	85 kA
Rated ultimate short-circuit breaking capacity Icu under 400V AC IEC 60947-2	50 kA
Rated ultimate short-circuit breaking capacity Icu under 415V AC IEC 60947-2	50 kA
Range of the thermal adjustment	250 / 300 / 400 A
Rated ultimate short-circuit breaking capacity Icu under 220V AC IEC 60947-2	85 kA
Dimensions Depth of installed product	150 mm
Depth of installed product	150 mm
	150 mm 260 mm 140 mm
Depth of installed product Height of installed product	260 mm
Depth of installed product Height of installed product Width of installed product	260 mm
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power	260 mm 140 mm 50 to 60 Hz
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In	260 mm 140 mm 50 to 60 Hz
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss per pole at 0.8*In	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss per pole at 0.8*In Total power loss at 0.63*In	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W 46 W
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss at 0.63*In Total power loss at 0.8*In	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W 46 W 74.2 W
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss per pole at 0.8*In Total power loss at 0.63*In Total power loss at 0.8*In Total power loss at 0.8*In	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W 46 W 74.2 W 116 W
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss per pole at 0.8*In Total power loss at 0.63*In Total power loss at 0.8*In Total power loss per pole at In	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W 46 W 74.2 W
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss per pole at 0.8*In Total power loss at 0.63*In Total power loss at 0.8*In Total power loss per pole at In	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W 46 W 74.2 W 116 W
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss per pole at 0.8*In Total power loss at 0.63*In Total power loss at 0.8*In Total power loss at 0.8*In	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W 46 W 74.2 W 116 W
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss per pole at 0.8*In Total power loss at 0.63*In Total power loss at 0.8*In Total power loss at 0.8*In Total power loss at 0.8*In Total power loss under IN Power loss per pole at In Tripping Time of response when opening Installation, mounting	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W 46 W 74.2 W 116 W 38.7 W
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss per pole at 0.8*In Total power loss at 0.63*In Total power loss at 0.8*In Total power loss at 10.8*In Total power loss at 10.8*In Total power loss at 10.8*In Total power loss under IN Power loss per pole at In Tripping Time of response when opening Installation, mounting Tightening torque	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W 46 W 74.2 W 116 W 38.7 W
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss per pole at 0.8*In Total power loss at 0.63*In Total power loss at 0.8*In Total power loss at 10.8*In Total power loss at 10.8*In Total power loss at 10.8*In Total power loss under IN Power loss per pole at In Tripping Time of response when opening Installation, mounting Tightening torque DIN rail mounting with optional adaptator	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W 46 W 74.2 W 116 W 38.7 W 10 ms
Depth of installed product Height of installed product Width of installed product Frequency Frequency Power Power loss per pole at 0.63*In Power loss per pole at 0.8*In Total power loss at 0.63*In Total power loss at 0.8*In Total power loss at 10.8*In Total power loss at 10.8*In Total power loss at 10.8*In Total power loss under IN Power loss per pole at In Tripping Time of response when opening Installation, mounting Tightening torque	260 mm 140 mm 50 to 60 Hz 15.3 W 24.7 W 46 W 74.2 W 116 W 38.7 W

Connection	
Connection	Front connection
Type of connection	Terminal
Protection	
Instantaneous protection (Ii): type	fixed
Cable	
Cable Material	Cu
Settings	
Range of the magnetic adjustment	2000 / 2400 / 2800 / 3200 / 3600 / 4000 A
Magnetic protection nob setting xIN	5/6/7/8/9/10
Equipment	
Number of auxiliary contacts as normally closed contact	0
Number of auxiliary contacts as normally open contact	0
Number of auxiliary contacts as change- over contact	0
Motor drive optional	Yes
Can be accessorized	Yes
Use cases	
Category of use	А
Standards	
Standard text	IEC 60947-2
European directive WEEE	concerned
Safety	
Protection index IP	IP4X
REACH conform	Yes
RoHS conform	Yes
Halogen free	No
Use conditions	
Degree of pollution according to IEC 60664 / IEC 60947-2	3
Altitude	2000 m
temperatur	
-	

50 °C

Temperature of calibration