



HMS160DC

Moulded Case Circuit Breaker h3+ P160 TM ADJ 3P3D 160A 50kA CTC

Technical characteristics

Architectu	re
------------	----

Type of order	Toggle
Neutral position	without neutral
Number of protected poles	3
Number of poles	3 P
Type of pole	3P3D
Type of case	Fixed built-in
Functions	
Complete device with protection unit	Yes
Reversing switch	No
Version as main switch	Yes
Version as emergency stop installation	No
Version as safety switch	No
Version as maintenance-/service switch	Yes
Trip Unit	TM A/A
Integrated earth fault protection	No
Controls and indicators	
Motor drive integrated	No
Main electrical features	
Rated operational voltage Ue	220 / 690 V
Type of supply voltage	AC
Frequency	50/60 Hz
Voltage	
Rated insulation voltage	800 V
Rated impulse withstand voltage	8 kV
With under voltage release	No
Electric current	
Rated current	160 A
Rated ultimate short-circuit breaking capacity Icu under 690V AC IEC 60947-2	6 kA
Thermal protection nob setting xIN	0.63 / 0.8 / 1
Rating current 10°C according to IEC 60947	192.1 A
Rating current 15°C according to IEC 60947	188.4 A
Rating current 20°C according to IEC 60947	184.6 A
Rating current 25°C according to IEC 60947	180.7 A

Rating current 30°C according to IEC 60947	176.8 A
Rating current 35°C according to IEC 60947	172.7 A
Rating current 40°C according to IEC 60947	168.6 A
Rating current 45°C according to IEC 60947	164.4 A
Rating current 50°C according to IEC 60947	160 A
Rating current 55°C according to IEC 60947	155.5 A
Rating current 60°C according to IEC 60947	150.9 A
Rating current 65°C according to IEC 60947	146.2 A
Rating current 70°C according to IEC 60947	141.2 A
Rated service breaking capacity lcs under 660V AC according IEC 60947-2	6 kA
Breaking capacity on 1 pole for IT 230V NF 60947-2	6 kA
Breaking capacity on 1 pole for IT 400V NF 60947-2	6 kA
Breaking capacity on 1 pole for IT 415V NF 60947-2	6 kA
Breaking capacity on 1 pole for IT 690V NF 60947-2	2.5 kA
Rated ultimate short-circuit breaking capacity Icu under 230V AC IEC 60947-2	65 kA
Rated ultimate short-circuit breaking capacity Icu under 240V AC IEC 60947-2	65 kA
Rated ultimate short-circuit breaking capacity Icu under 400V AC IEC 60947-2	50 kA
Rated ultimate short-circuit breaking capacity Icu under 415V AC IEC 60947-2	50 kA
Range of the thermal adjustment	100 / 125 / 160 A
Rated service breaking capacity Ics under 110-138V AC according IEC 60947-2	65 kA
Rated ultimate short-circuit breaking capacity Icu under 220V AC IEC 60947-2	65 kA
Rated ultimate short-circuit breaking capacity Icu under 380V AC IEC 60947-2	50 kA
Rated ultimate short-circuit breaking capacity Icu under 660V AC IEC 60947-2	6 kA
Dimensions	
Depth of installed product	97 mm
Height of installed product	130 mm
Width of installed product	90 mm
Frequency	
Frequency	50 to 60 Hz
Power	
Power loss per pole at 0.63*In	5.78 W
Power loss per pole at 0.8*In	9.02 W
Total power loss at 0.63*In	17.33 W
Total power loss at 0.8*In	27.07 W
Total power loss under IN	42.3 W
Power loss per pole at In	14.1 W
Tripping	

Short-time delayed tripping	N
Endurance	
Electric endurance in number of cycles	1000
Number of mechanical operations	4000
Cover, door	
Interlockable	Ye
Installation, mounting	
Tightening torque	6N
DIN rail mounting with optional adaptator	Ye
Suitable for front mounting center	N
Suitable for front mounting	N
Suitable for ground mounting	Ye
Connection	
Connection cross-sect. flexible conductor	6 / 70mn
Connection cross-sect. rigid cable	6 / 95mn
Connection	Front connection
Protection	
Instantaneous protection (Ii): type	fixe
Instantaneous protection (Ii): type Cable	fixe
Cable Cable Material	
Cable Cable Material Settings	C
Cable Cable Material Settings Range of the magnetic adjustment	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as normally open contact	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Can be accessorized	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Can be accessorized Use cases	960 / 1120 / 1280 / 1440 / 1600
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Can be accessorized Use cases Category of use	960 / 1120 / 1280 / 1440 / 1600 6 / 7 / 8 / 9 / 1
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Can be accessorized Use Use	960 / 1120 / 1280 / 1440 / 1600 6 / 7 / 8 / 9 / 1
Cable Cable Material Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Can be accessorized Use cases Category of use Vibrations and shocks withstand	M Ye IEC 68068-2-52 Test F

REACH conform	Yes
RoHS conform	Yes
Halogen free	No
Use conditions	
Degree of pollution according to IEC 60664 / IEC 60947-2	3
Altitude	2000 m
Air humidity protection	95%HR 55°C sev Kn (IEC 68-2-30/52)
temperatur	
Temperature of calibration	50 °C