



quickconne

Yearly time switch 2 channels, digital, 4 modules

Technical characteristics

| Function | Presence simulation ; Keylock via PIN code ; with operating hours meter ; with pulse function | |
|--|---|--|
| Main electrical features | | |
| Rated operational voltage Ue | 230 \ | |
| Frequency | 50/60 H. | |
| Dimensions | | |
| Depth of installed product | 69 mn | |
| Height of installed product | 90 mn | |
| Width of installed product | 70 mn | |
| Power | | |
| Power consumed | 2 V/ | |
| Total power loss under IN | 2 V | |
| Battery | | |
| Development for a set | - | |
| Power reserve [years] | ≈ 5 ∂ | |
| | ≈ 5 8 | |
| Power reserve [years] Incandescent bulbs control | | |
| Incandescent bulbs control | | |
| Incandescent bulbs control Max. power with incandescent lamps | | |
| Incandescent bulbs control Max. power with incandescent lamps Installation, mounting | 1500 V | |
| Incandescent bulbs control Max. power with incandescent lamps Installation, mounting Mounting type | 1500 V | |
| Incandescent bulbs control Max. power with incandescent lamps Installation, mounting Mounting type Connection | 1500 V din-Ra | |
| Incandescent bulbs control Max. power with incandescent lamps Installation, mounting Mounting type Connection Connection cross-sect. flexible conductor | 1500 V din-Ra 0,75 / 2,5mm | |
| Incandescent bulbs control Max. power with incandescent lamps Installation, mounting Mounting type Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable | 1500 V din-Rai 0,75 / 2,5mm 0,75 / 2.5mm | |
| Incandescent bulbs control Max. power with incandescent lamps Installation, mounting Mounting type Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection | 1500 V din-Ra 0,75 / 2,5mm 0,75 / 2.5mm quick connec | |
| Incandescent bulbs control Max. power with incandescent lamps Installation, mounting Mounting type Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Number of contacts | 1500 V din-Ra 0,75 / 2,5mm 0,75 / 2.5mm quick connec | |
| Incandescent bulbs control Max. power with incandescent lamps Installation, mounting Mounting type Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Number of contacts Type of contacts | 1500 V din-Ra 0,75 / 2,5mm 0,75 / 2.5mm quick connec 2 changeover + 2NC | |
| Incandescent bulbs control Max. power with incandescent lamps Installation, mounting Mounting type Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Number of contacts Type of contacts Type of connection | 1500 V din-Ra 0,75 / 2,5mm 0,75 / 2.5mm quick connec 2 changeover + 2NC | |
| Incandescent bulbs control Max. power with incandescent lamps Installation, mounting Mounting type Connection Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Type of connection Number of contacts Type of contacts Type of connection Settings | 1500 V din-Rai 0,75 / 2,5mm 0,75 / 2.5mm quick connec 2 changeover + 2NC with QuickConnect plug-in terminals | |
| | ≈ 5 a 1500 W din-Rai 0,75 / 2,5mm 0,75 / 2.5mm quick connect 2 changeover + 2NC with QuickConnect plug-in terminals automatic 1 mm | |

Equipment

| Number of channels | 2 |
|------------------------|---------------|
| Supply failure reserve | 5 years |
| Use | |
| Cycle | yearly |
| Safety | |
| Protection index IP | IP20 |
| Use conditions | |
| Operating temperature | -1050 °C |
| Working accuracy | + 0,2 s / 24h |