



EH111



## Time switch daily cycle with reserve

Functions	
Power reserve	≈ 200 h
Configuration	
Switch mode	change-over contact, usable as NC or NC
Main electrical features	
Frequency	50 Hz
Dimensions	
Depth of installed product	60 mm
Height of installed product	90 mm
Width of installed product	54 mm
Power	
Power consumed	0.5 VA
Power consumption (operation)	0.5 VA
Total power loss under IN	1 W
Power dissipation per coil	0.5 W

## Charging time of the power reserve in hours 120

Incandescent bulbs control	
Max. power with incandescent lamps	900 W

## Installation, mounting

Mounting type	surface-mounted

1 / 4mm²
1 / 4mm²
with screw
1
1 changeover
with screw terminals

Settings	
Summer / Winter time change	manual
Shortest switching time	15 mn
Type of programming	analog

Programming cycle	24H
Setting	Setting via day dial
Equipment	
Number of channels	1
Supply failure reserve	200 h
Use	
Cycle	daily
Use conditions	
Operating temperature	-1055 °C
Working accuracy	1