



TRE221

**IP55** 

**Module 1 output for shutter/blind 10A IP55 KNX radio QL**

**Technical characteristics**

**Architecture**

Bus system	KNX
Number of blinds/shutters outputs	1

**Functions**

Function	reset function (to factory setting) ; Repeat function can be activated to increase the radio range ; easy additional functions: +6 scenes
----------	-------------------------------------------------------------------------------------------------------------------------------------------

**Configuration**

Switch mode	with 2 mechanically and electrically mutually-locked relay contacts
-------------	---------------------------------------------------------------------

**Controls and indicators**

Indicator lamp	yes
----------------	-----

**Connectivity**

Bus system radio frequent	Yes
---------------------------	-----

**Main electrical features**

Frequency	50 Hz
Type of supply voltage	AC

**Voltage**

Operating voltage	230 V AC
-------------------	----------

**Dimensions**

Height	35 mm
Width	85 mm

**Power**

Contact rating with 230 V in AC1	2000 W
----------------------------------	--------

**Materials**

Surface appearance	matt
--------------------	------

**Connection**

Type of connection	with screw
Type of connection	with screw-in lift terminals

**Use conditions**

Operating temperature	-10...55 °C
-----------------------	-------------