




TRE400



Module 1 input + 1 output, 10A, IP55, KNX radio

Technical characteristics

Architecture

| | |
|-----------------------------------|-----|
| Bus system | KNX |
| Number of blinds/shutters outputs | 0 |

Functions

| | |
|----------|---|
| Function | easy additional functions: +6 scenes ; Repeat function can be activated to increase the radio range ; reset function (to factory setting) |
|----------|---|

Controls and indicators

| | |
|----------------|-----|
| Indicator lamp | yes |
|----------------|-----|

Connectivity

| | |
|---------------------------|-----|
| Bus system radio frequent | Yes |
|---------------------------|-----|

Main electrical features

| | |
|------------------------|----|
| Type of supply voltage | AC |
|------------------------|----|

Voltage

| | |
|-------------------|----------|
| Operating voltage | 230 V AC |
|-------------------|----------|

Dimensions

| | |
|--------|-------|
| Height | 35 mm |
| Width | 85 mm |

Reach distance

| | |
|-------------------------|--------------------------------|
| Max. transmission range | 30m in house / 100m free field |
|-------------------------|--------------------------------|

Materials

| | |
|--------------------|------|
| Surface appearance | matt |
|--------------------|------|

Equipment

| | |
|--------------------|---|
| Number of channels | 1 |
|--------------------|---|

Use conditions

| | |
|-----------------------|-------------|
| Operating temperature | -10...55 °C |
|-----------------------|-------------|