




TX211A



Dimmer 3 outputs KNX, 1/10V

Technical characteristics

Architecture

Bus system KNX

Controls and indicators

Indicator lamp yes

Connectivity

Bus system radio frequent No

Main electrical features

Frequency 50 Hz

Power

Total power loss under IN 9 W

Materials

Colour stone grey

Connection

Connection cross-sect. flexible conductor 1 / 6mm²

Connection cross-sect. rigid cable 1,5 / 10mm²

Type of load universal

Settings

Setting basic brightness programmable

Use conditions

Operating temperature 0...45 °C