



TXA025

## Twilight switch 1-6 channels KNX, 20kLux

### Technical characteristics

#### Architecture

Fixing mode Din-Rail

#### Functions

Function for switch, dimmer and shutter functions

#### Power

Total power loss under IN 0.3 W

#### Materials

Colour stone grey

#### Lighting control

Brightness measurement range 2 / 20000 Lux

#### Connection

Type of connection with screw terminals

#### Settings

Setting Brightness modifiable via potentiometer

#### Equipment

Number of channels 1

#### Safety

Protection index IP IP30

#### Use conditions

Operating temperature 0...45 °C