



TXA210N

Dimmer 1 channel 600W

Technical characteristics

Arch	itecture	

Bus system KNX

Controls and indicators

Indicator lamp yes

Power

Incandescent bulb power	20 / 600 W
Total power loss under IN	4.8 W

Connection

Connection cross-sect. flexible conductor	0,75 / 2,5mm ²
Connection cross-sect. rigid cable	0,75 / 2.5mm²
Type of load	universal

Use conditions

Operating temperature $0...45~^{\circ}\text{C}$