



WFQXBSB



Quadplexer TV, FM/DAB, Satellite 1 & Satellite 2 Outlet Brushed

Technical characteristics

Connectivity

| | |
|---------------|----------------|
| Mounting type | Screw mounting |
|---------------|----------------|

Attenuation

| | |
|----------------------|---------|
| Tap loss at 2150 MHz | 1.50 dB |
| Tap loss at 860 MHz | 2.50 dB |

Frequency

| | |
|---------------------|---------------|
| Frequency bandwidth | 5 - 2,400 MHz |
|---------------------|---------------|

Equipment

| | |
|-------------------|---|
| Number of outputs | 4 |
|-------------------|---|

Materials

| | |
|----------|-----------------|
| Material | Stainless steel |
| Colour | Stainless steel |

Installation, mounting

| | |
|-------------|----------------|
| Mounting on | Flush mounting |
|-------------|----------------|

Identification

| | |
|----------------------|-------------------------------------|
| Assembly arrangement | Basic element with full cover plate |
|----------------------|-------------------------------------|