:hager

Consumer Unit Design 10 Flush Configurable

For the distribution of power in a residential application, conforming to BS EN 61439-3 including Annex ZB (16kA rating).

Design 10 has been created as an entry level board which meets the requirements of the wiring regulations (BS 7671) and allows the consumer unit to be installed flush at the height stated in the building regulations (Part M), with minimum impact on the area.

Regulation 421.1.201 within domestics (household) applications consumer units and similar assemblies shall comply with BS EN 61439-3 and shall have their enclosure manufactured from a non-combustible material.

Regulation 411.3.3 additional protection by means of a 30mA RCD.

Regulation 314.1&2 segregation of circuits to avoid danger and minimise inconvenience in the event of a fault.

Regulation 522.6.202 protection of wiring concealed in walls or partitions with RCD 30mA.

Regulation 531.3.3 Selection of appropriate RCD. Type A RCCBs can detect and respond to both AC and pulsating DC components.

Regulation 536.4.3.2 & 536.4.202 overload protection of switches and RCCBs. For installations where the upstream overcurrent protection is less than or equal to 100 A

A configurable board allows the installer flexibility to separate the circuits across the two RCCBs without being forced to maintain an even number of circuits across each device.

The flush design removes the harsh appearance of a surface mounted enclosure on the wall.







VMLF910C

MTN1**

Description

Size	Cat Ref.
4	VMLF910C
5	VMLF912C
7	VMLF916C
	4 5 7

Devices

MCB 6A - 63A (Marked Rated Current on Device)

Features & Benefits

- Cable clamp Secures supply cables on entry to main incoming device preventing any movement being transmitted through meter tails to device
- Rear Knockouts for ease of cable entry Cable protector plate (VM02CE) provided
- 2 piece base allows for first fix, second fix option
- Adjustable Depth Base Base assembly is adjustable from 72mm to 92mm, at 72mm allows for 60mm studwork and 12mm plasterboard
- Full metal DIN rail Secure and stable attachment of devices
- Quick release clip on MCB/RCBO Allows removal of MCB/RCBO with busbar still in place
- Optimised cabling space DIN rail position allows maximum cabling space
- Top mounted terminal rail makes the wiring of the neutral and earth connections neat and simple.
- Torque settings displayed inside front cover so they're easily accessible by the electrician.

:hager

Technical Characteristics

Standards	BS EN 61439-3		
Classification	Consumer Unit		
Rated & Operational Voltage (Un/Ue)	230V a.c 50 Hz		
Rated Insulation Voltage (Ui)	320V a.c. 50Hz		
Rated Frequency (fn)	50 Hz		
Rated impulse withstand voltage (Uimp)	4kV		
Rated Current of the Assembly (Ina)	100A		
Rated Current of an Outgoing Circuit I _n C	MTN1** MCB (Marked Rated Current on Device)		
Rated Conditional Short Circuit of the Assembly (I_{CC})	Annex ZB: 16kA rms at 250V, power factor 0.6 with equipment and arrange- ments specified in Hager's technical documentation/catalogue		
Protection against electric shock	Consumer Unit shall be installed in an electrical system conforming to IEC 60364 / BS 7671		
Rated Diversity Factor (RDF) / Values of assumed loading	10 way and above - 0.5		
Note: RDF only applies to continuously and simultaneously loaded circuit			
In principle, this means adjacent circuit breakers having a load on time ex the 'on' time will need to have the rated diversity factor applied as indicate	cceeding 30 minutes or where a load not exceeding 30 minutes has an 'off' time less than ed.		
the 'on' time will need to have the rated diversity factor applied as indicate			
the 'on' time will need to have the rated diversity factor applied as indicate	ed. 2		
the 'on' time will need to have the rated diversity factor applied as indicate Pollution Degree Types of System Earthing for which the assembly is designed	ed. 2		
the 'on' time will need to have the rated diversity factor applied as indicate Pollution Degree	ed. 2 TNC-S and TN-S when installed in an electrical system conforming to BS 7671		
the 'on' time will need to have the rated diversity factor applied as indicate Pollution Degree Types of System Earthing for which the assembly is designed Intended locations Stationary assembly	ed. 2 TNC-S and TN-S when installed in an electrical system conforming to BS 7671		
the 'on' time will need to have the rated diversity factor applied as indicate Pollution Degree Types of System Earthing for which the assembly is designed Intended locations Stationary assembly Degree of protection	ed. 2 TNC-S and TN-S when installed in an electrical system conforming to BS 7671 Indoor use only IP2XC with door open / closed and full compliment of devices / blanks fitted. Note: Where cables are installed through the top wall of the enclosure, gaps of		
the 'on' time will need to have the rated diversity factor applied as indicate Pollution Degree Types of System Earthing for which the assembly is designed Intended locations Stationary assembly Degree of protection Intended use	ed. 2 TNC-S and TN-S when installed in an electrical system conforming to BS 7671 Indoor use only IP2XC with door open / closed and full compliment of devices / blanks fitted. Note: Where cables are installed through the top wall of the enclosure, gaps of IP4X to be maintained.		
the 'on' time will need to have the rated diversity factor applied as indicate Pollution Degree Types of System Earthing for which the assembly is designed Intended locations Stationary assembly Degree of protection Intended use Electromagnetic compatibility (EMC) classification	ed. 2 TNC-S and TN-S when installed in an electrical system conforming to BS 767 Indoor use only IP2XC with door open / closed and full compliment of devices / blanks fitted. Note: Where cables are installed through the top wall of the enclosure, gaps of IP4X to be maintained. Intended for use in domestic (residential) or similar premises		
the 'on' time will need to have the rated diversity factor applied as indicate Pollution Degree Types of System Earthing for which the assembly is designed Intended locations Stationary assembly Degree of protection Intended use Electromagnetic compatibility (EMC) classification External design	ed. 2 TNC-S and TN-S when installed in an electrical system conforming to BS 767 Indoor use only IP2XC with door open / closed and full compliment of devices / blanks fitted. Note: Where cables are installed through the top wall of the enclosure, gaps of IP4X to be maintained. Intended for use in domestic (residential) or similar premises EMC environment B		
the 'on' time will need to have the rated diversity factor applied as indicate Pollution Degree Types of System Earthing for which the assembly is designed Intended locations Stationary assembly Degree of protection Intended use Electromagnetic compatibility (EMC) classification External design Mechanical impact protection	ed. 2 TNC-S and TN-S when installed in an electrical system conforming to BS 767 Indoor use only IP2XC with door open / closed and full compliment of devices / blanks fitted. Note: Where cables are installed through the top wall of the enclosure, gaps of IP4X to be maintained. Intended for use in domestic (residential) or similar premises EMC environment B Wall mounted, surface type, enclosed assembly.		
the 'on' time will need to have the rated diversity factor applied as indicate Pollution Degree Types of System Earthing for which the assembly is designed Intended locations	ed. 2 TNC-S and TN-S when installed in an electrical system conforming to BS 767 Indoor use only IP2XC with door open / closed and full compliment of devices / blanks fitted. Note: Where cables are installed through the top wall of the enclosure, gaps of IP4X to be maintained. Intended for use in domestic (residential) or similar premises EMC environment B Wall mounted, surface type, enclosed assembly. IK05		

Warranty - Hager undertakes to replace or repair at its discretion products should they become inoperable within the time periods as stated - 2 Years.

Accessories

38mm Open Grommet	Allows protection of cables entering top or bottom of the enclosure	VMGROM
Grommet strip	For protecting cables against damage when entering the board	VM05GS

Flush Design 10 Dimensions (mm)

	Enclosure Size			
	4	5	7	
Height	282	282	282	
Width	335	407	515	
С	32	32	32	
D	298	370	478	
E	252	252	252	
F	72	72	72	

		Number of Knockouts		
	Top Face 50 x 20 (mm)	4	5	7
\bigcirc	Bottom Face 50 x 20 (mm)	4	5	7
\bigcirc	Back 100 x 50 (mm)	2	2	3
\bigcirc	Left Face 20.8 (mm)	1	1	1

